

Gewa Andromeda

latest generation remote control receiver



Well-known for long range and high reliability





GEWA ANDROMEDA

is a further development of the familiar Gewalink system, well-known for long range and high reliability.

Gewa Andromeda is unique in combining infrared (IR) and radio (Gewa Radio) in the same receiver.

Gewa Andromeda has been designed to be easy to program, but it also has a number of advanced functions such as a mono/bistable function, switchon display, and max/min response time.

It is possible to connect up to 5 separate IR detectors. It is also possible to connect external control switches for activating the relays.

GEWA ANDROMEDA IS AVAILABLE IN THE FOLLOWING MODELS

RECEIVER

Art.nr 419830 Andromeda IRZ-REC 4 IR and radio receiver for indoor installation. 4 relay outputs.

Art.nr 419835 Andromeda IRZ-REC 4 OUT IR and radio receiver for outdoor installation. 4 relay outputs.

Art.nr 419850 Andromeda IRZ-REC 4 WM IR and Radio receiver for indoor installation. 4 relay outputs. Specially adapted for window openers

Art.nr 419812 Andromeda IR-REC 2 IR Receiver for indoor installation. 2 relay output. Without radio.

IR DETECTORS

Art.nr 419860 Andromeda IR-DET 3 IR detector for indoor and outdoor installation. 3 meter cable.

Art.nr 419865 Andromeda IR-DET 15 IR detector for indoor and outdoor installation. 15 meter cable.

Art.nr 419870 Andromeda IR-DET IR detector for indoor installation. Without cable.

TECHNICAL DATA

Operating voltage:

Max power consumption at rest:

Max power consumption: Max relay load:

Max detectors:

Programming channels:

Ambient temperature:

12-24 V AC/DC (- 10% - +20%)

60mA (2 detectors, inactive relays, active radio)

120mA (2 detectors, 4 active relays, active radio)

3A, 24V AC/DC resistive load 6 including built-in detector

GewaLink channels 0–127, 4096 code and Gewa Radio

-20°C - +35°C

> MORE INFORMATION: visit our homepage

